

CHAPTER 17

Online Status

17.1 Introduction

The **Online Status** provides some useful information about the Vigor router, ISDN, LAN and WAN interface. Also, you could use the status page to know the Internet access status.

17.2 Online Status Descriptions

Click **Online Status** to open the Online Status page. Herein, We use an example to explain **the Online Status**. In the example, as shown in the following picture, the router is working on Dynamic IP mode to access the Internet.

17.2.3 WAN Status:

Mode: Indicate which ADSL access mode is active. Depending upon the ADSL access mode, you may see **PPPoE**, **PPPoA**, or **MPoA**.

GW IP Addr: The gateway IP address.

IP Address: IP address of the WAN interface.

TX Packets: Total number of transmitted IP packets during this connection session.

TX Rate: Transmission rate in characters per second (cps) for outgoing data.

RX Packets: Total number of received IP packets during this connection session.

RX Rate: Reception rate in characters per second (cps) for incoming data.

Up Time: Connection time. The format is HH:MM:SS, where HH, MM, and SS, indicate hours, minutes, and seconds, respectively.

Drop PPPoE or PPPoA: Click the link to disconnect the PPPoE or PPPoA connection.

17.2.4 ISDN Status: (Vigor2900i and Vigor2900Gi only)

Active Connection: The ISP, active remote ISDN dial-in user, or LAN-to-LAN connection name and also the IP address for each B channel.

TX Pkts: Total number of transmitted IP packets during this connection session.

TX Rate: Transmission rate in characters per second (cps) for outgoing data.

RX Pkts: Total number of received IP packets during this connection session.

RX Rate: Reception rate in characters per second (cps) for incoming data.

Online Status

Up Time: Connection time. The format is HH:MM:SS, where HH, MM, and SS represent hours, minutes, and seconds, respectively.

Drop B1: Click to disconnect the B1 channel.

Drop B2: Click to disconnect the B2 channel.